



- 4 2/1 high performance Bench-type DMM, Liquid crystal display.
- It can be used to measure DC and AC Voltage, DC and AC current, Resistance, Capacitance, Hz, hFE, Diodes and Continuity.
- The max. voltage measuring can up to 1000V DC or AC peak value. Resolution can be 10u V, and current measuring can up to 20A, it also has the function of polarity auto-change, backlight displaying and directly reading.
- For AC measuring, it is performed by high accuracy true RMS, has the feature of width measuring and to get accurate rms for AC flow of any wave shape.

## Technical data

Basic function	Range	Basic Accuracy
DC Voltage	200mV/2V/20V/200V/1000V	$\pm(0.05\%+3)$
AC Voltage	200mV/2V/20V/200V/750V	$\pm(0.8\%+80)$
DC Current	20mA/200mA/2A/20A	$\pm(0.35\%+10)$
AC Current	200mA/2A/20A	$\pm(0.8\%+80)$
Resistance	200 $\Omega$ /2k $\Omega$ /20k $\Omega$ /200k $\Omega$ /2M $\Omega$ /20M $\Omega$	$\pm(0.1\%+5)$
Frequency	20kHz/200kHz	$\pm(1.0\%+20)$
Capacitance	20nF/2uF/200uF	$\pm(3.5\%+20)$

Special Function	
Diode test	✓
Triode test	✓
Continuity buzzer	✓
Overload protection	✓
Input impedance	10 M $\Omega$
AC frequency response	3 times/s
Sampling rate	40~50kHz
Operation way	Manual range
Max. Display	19999
Dimension	245×220×82mm
Weight	Approx:1Kg
Power	AC220V/110V 50Hz/60Hz